Radio chime Euro plug 230 V Language German white CALIMA + radio transmitter flush-mounted - for mechanical push-buttons

Product number 1249-400E-UP



Product description

Radio chime Euro plug 230 V Language German white CALIMA + radio transmitter flush-mounted - for mechanical buttons

With the CALIMA radio chime Euro plug + radio transmitter, classic wired doorbell systems can be modernised into a radio bell system without having to change the bell push on the front door. Suitable for many of our doorbells and letterboxes. This set is suitable for 1 bell push (up to 11 push buttons/radio transmitters UP possible per receiver). A further set must be used for each additional party.

Placed discreetly in a socket, CALIMA 400 announces your visit anywhere in the house. And illuminates your way at night with the integrated night light. The wireless chime can be placed in a socket anywhere in the house. Thanks to its long range, CALIMA 400 reliably announces your visitors or suppliers even at a greater distance from the radio transmitter.

Briefkasten Manufaktur Lippe GmbH
Werler Straße 60
32105 Bad Salzuflen

www.briefkasten-manufaktur.de
info@briefkasten-manufaktur.de
Tel.: +49 5222 807110

Geschäftsführer Oliver Woineck
Ust.ID.Nr. DE303690847
Handelsregister Amtsgericht Lemgo, HRB 8618

- **Plug-in radio chime 230 V type: GROTHE Calima 400E series**
- Radio chime for plugging into sockets.
- Receiver dimensions: Ø 60 mm x 95 mm incl. plug
- Power supply: 100 - 240 V, 50/60 Hz
- Colour: White silk matt / black
- Volume: Max. 83 dB(A) adjustable
- Number of melodies: 13 polyphonic melodies
- Frequency: 868.35 MHz
- Optical signalling: LED ring in various colours and adjustable flashing light
- Night light: Various colours can be set
- Call differentiation: 11-fold
- Number of linkable transmitters: 11
- Call types: Central, individual, matrix call
- **Radio transmitter UP type: GROTHE Mistral series**
- Radio transmitter dimensions: 42 x 40 x 12 mm (WD)
- Power supply: 12 V DC or 1 CR 2450 battery (not included)
- Frequency: 868.35 MHz
- Protection class: IP20 (to be installed in a protected area)
- Language: German

- **150 metre range**
- The interference-free radio connection up to 150 metres guarantees a reliable door chime.
- **13 polyphonic melodies**
- With the large selection of appealing ringtones, you can customise your Calima 400 flexibly.
- **Multiple call differentiation for several doors**
- With the help of call differentiation, you can immediately recognise whether the front door or the garden gate has rung. Up to 11 wireless bell buttons can be programmed and 11 can be assigned an individual ring tone.
- **Optical LED signal**
- LED ring with colour selection for visual signalling and night light function.
- **Adjustable night light function**
- Night light in desired colour.
- **Menu navigation with voice prompt**
- Each menu step is played back to you as a voice announcement.

Installation

- 1. install the MISTRAL radio transmitter in a flush-mounted box or the function box behind the existing bell button
- 2. pair the MISTRAL radio transmitter with the radio chime receiver
- 3. by pressing the existing bell button, the radio transmitter sends a signal to the radio chime receiver.

Notes

- Walls, doors, metal parts etc. can noticeably reduce the range!

Dimensions

Width in mm	60
Height in mm	60
Total width in mm	60
Depth in mm	95,0

Briefkasten Manufaktur Lippe GmbH
Werler Straße 60
32105 Bad Salzuflen

www.briefkasten-manufaktur.de
info@briefkasten-manufaktur.de
Tel.: +49 5222 807110

Geschäftsführer Oliver Woineck
Ust.ID.Nr. DE303690847
Handelsregister Amtsgericht Lemgo, HRB 8618

More images


GROTHE
URMET GROUP
Grothe GmbH
Löhestraße 22
D-53773 Hennef
MISTRAL SE06
8- 12 V DC / 30 mA
868 MHz
Batt. CR2450




GROTHE


GROTHE


E230968 94V-0
GET-I 2026


STECKDOSEN-FUNKGONG
Lautsprecher
Auswahl-taste
Menü-taste
LED-Lichtring
Eurostecker