

Gira extension module for built-in loudspeaker

Product number 125900



Product description

Gira extension module for built-in loudspeaker

Module for extending the built-in loudspeaker if more than eight mechanical bell buttons are to be connected.

- Up to twelve mechanical bell buttons can be connected.
- Further bell buttons can be connected via additional extension modules.
- Up to eleven extension modules can be connected to one built-in loudspeaker.
- AC voltage monitoring of the bell button connections to prevent oxidation on the button contacts.
- Small design.
- Protection of the connection terminals against incorrect connection.
- The extension module can be attached using screws or adhesive.
- The fixing material is included in the scope of delivery.

Technical data

Connections

mech. bell push: 12 x screw terminal

Common earth of the bell buttons: 1 x screw terminal

Connection cable: 2 x connector strip

Ambient temperature: -25 °C to +70 °C

Protection class: IP44

Notes

- This component can be used to set up door communication systems with up to 140 audio users (e.g. 1 x built-in loudspeaker, 11 x extension module for built-in loudspeaker, 136 x surface-mounted home station).

Dimensions

Width in mm 67

Height in mm 56 | incl. mounting bracket 66.4

Depth in mm 27,0

Weight in kg 0,2