

Radio chime Bluetooth microSD rechargeable battery language EN white CALIMA + radio transmitter UP - for mechanical buttons

Product number 1249-800E-UP



Product description

Wireless chime Bluetooth microSD rechargeable battery Voice EN white CALIMA + wireless transmitter UP - for mechanical buttons

With the CALIMA wireless chime Bluetooth microSD battery + wireless transmitter, classic wired doorbell systems can be modernised into a wireless doorbell system without having to change the bell push on the front door. Suitable for many of our doorbells and letterboxes. This set is suitable for 1 bell push (up to 11 push buttons/radio transmitters UP possible per receiver). An additional set must be used for each additional party.

Would you like to hear a specific melody when the doorbell rings? With a microSD card, MP3 files can be set as a chime melody on the CALIMA 800*. This way, CALIMA 800 announces your visit with your favourite song. Connected to your smartphone via BLUETOOTH®, the CALIMA 800 wireless chime becomes a portable loudspeaker that plays your music anywhere in the house. As soon as the doorbell rings, the music is interrupted and the doorbell sound is played. The music then continues to play. Thanks to its long range, CALIMA 800 reliably announces your visitors or suppliers even at a greater distance from the radio transmitter.

- **Plug-in radio chime 230 V type: GROTHE Calima 800E series**
- Radio chime with lithium battery and charging station with plug connection.
- Receiver dimensions: Ø90 x 140 mm
- Power supply: 1 x lithium battery with plug connection
- Colour: White silk matt / black
- Volume: Max. 86 dB(A) adjustable
- Number of melodies: 13 polyphonic melodies plus own melodies via SD card*
- Frequency: 868.35 MHz
- Optical signalling: LED ring in various colours and adjustable flashing light
- Call differentiation: 11-fold
- Number of linkable transmitters: 11
- Call types: central, individual, matrix call
- **Radio transmitter UP type: GROTHE Mistral series**
- Radio transmitter dimensions: 42 x 40 x 12 mm (WD)
- Power supply: 12 V DC or 1 CR 2450 battery (not included)
- Frequency: 868.35 MHz
- Protection class: IP20 (to be installed in a protected area)

- **Loudspeaker and door chime in one**
- When paired with a smartphone, the CALIMA 800 wireless chime becomes a portable BLUETOOTH® loudspeaker. As soon as the doorbell rings, the music is interrupted and the ringing melody is played.
- Battery life up to 8 hours (when music is playing).
- **Customised call melodies**
- Would you like to hear a specific melody when the doorbell rings? With a microSD card, MP3 files can be set as ringing melodies on the CALIMA 800*.
- **Menu navigation with voice prompt**
- All menu settings for the CALIMA 800 are made using two buttons. With the acoustic announcement, you always know which menu item you are in.
- **Visual LED signal**
- LED ring with colour selection for visual signalling.

Installation

- 1. install the MISTRAL radio transmitter in a flush-mounted box or the function box behind the existing bell button
- 2. pair the MISTRAL radio transmitter with the radio chime receiver
- 3. by pressing the existing bell button, the radio transmitter sends a signal to the radio chime receiver.

Notes

- Walls, doors, metal parts etc. can noticeably reduce the range!
- *MicroSD card not included in the scope of delivery.

Dimensions

Width in mm 90

Height in mm 140

Depth in mm 90,0

More images





spielt per BLUETOOTH® das Lieblingslied

