

# Radio chime Euro plug 230 V language DE white CALIMA + radio transmitter flush-mounted - for mechanical push-buttons

Codice articolo 1249-400E-UP



## Descrizione del prodotto

### Radio chime Euro plug 230 V language EN white CALIMA + radio transmitter flush-mounted - for mechanical buttons

With the CALIMA radio chime Euro plug + radio transmitter, classic wired doorbell systems can be modernised into a radio bell system without having to change the bell push on the front door. Suitable for many of our doorbells and letterboxes. This set is suitable for 1 bell push (up to 11 push buttons/radio transmitters UP possible per receiver). A further set must be used for each additional party.

Placed discreetly in a socket, CALIMA 400 announces your visit anywhere in the house. And illuminates your way at night with the integrated night light. The wireless chime can be placed in a socket anywhere in the house. Thanks to its long range, CALIMA 400 reliably announces your visitors or suppliers even at a greater distance from the radio transmitter.

- **Plug-in radio chime 230 V type: GROTHE Calima 400E series**
  - Radio chime for plugging into sockets.
  - Receiver dimensions: Ø 60 mm x 95 mm incl. plug
  - Power supply: 100 - 240 V, 50/60 Hz
  - Colour: White silk matt / black
  - Volume: Max. 83 dB(A) adjustable
  - Number of melodies: 13 polyphonic melodies
  - Frequency: 868.35 MHz
  - Optical signalling: LED ring in various colours and adjustable flashing light
  - Night light: Various colours can be set
  - Call differentiation: 11-fold
  - Number of linkable transmitters: 11
  - Call types: Central, individual, matrix call
- **Radio transmitter UP type: GROTHE Mistral series**
  - Radio transmitter dimensions: 42 x 40 x 12 mm (WD)
  - Power supply: 12 V DC or 1 CR 2450 battery (not included)
  - Frequency: 868.35 MHz
  - Protection class: IP20 (to be installed in a protected area)

- **150 metre range**
- The interference-free radio connection up to 150 metres guarantees a reliable door chime.
- **13 polyphonic melodies**
- With the large selection of appealing ringtones, you can personalise your Calima 400 with complete flexibility.
- **Multiple call differentiation for several doors**
- With the help of call differentiation, you can immediately recognise whether the front door or the garden gate has rung. Up to 11 wireless bell buttons can be programmed and 11 can be assigned an individual ring tone.
- **Optical LED signal**
- LED ring with colour selection for visual signalling and night light function.
- **Adjustable night light function**
- Night light in desired colour.
- **Menu navigation with voice prompt**
- Each menu step is played back to you as a voice announcement.

## Installation

- 1. install the MISTRAL radio transmitter in a flush-mounted box or the function box behind the existing bell button
- 2. pair the MISTRAL radio transmitter with the radio chime receiver
- 3. by pressing the existing bell button, the radio transmitter sends a signal to the radio chime receiver.

## Notes

- Walls, doors, metal parts etc. can noticeably reduce the range!

## Dimensioni

Larghezza in mm 60  
Altezza in mm 60  
Profondità in mm 95,0

## Altre immagini



