# Radio chime Euro plug 230 V Language German white CALIMA

**Product number** 1249-400E



## Product description

### Radio chime Euro plug 230 V Language German white CALIMA

Discreetly placed in a socket, CALIMA 400 announces your visit anywhere in the house. And illuminates your way at night with the integrated night light. The wireless chime can be placed in a socket anywhere in the house. Thanks to its long range, CALIMA 400 reliably announces your visitors or suppliers even at a greater distance from the radio transmitter.

- **Plug-in radio chime 230 V type: GROTHE Calima 400E series**
- Radio chime for plugging into sockets.
- Receiver dimensions: Ø 60 mm x 95 mm incl. plug
- Power supply: 100 - 240 V, 50/60 Hz
- Colour: White silk matt / black
- Volume: Max. 83 dB(A) adjustable
- Number of melodies: 13 polyphonic melodies
- Frequency: 868.35 MHz
- Optical signalling: LED ring in various colours and adjustable flashing light
- Night light: Various colours can be set
- Call differentiation: 11-fold
- Number of linkable transmitters: 11
- Call types: Central, individual, matrix call
- Language: German

Briefkasten Manufaktur Lippe GmbH
Werler Straße 60
32105 Bad Salzuflen

www.briefkasten-manufaktur.de
info@briefkasten-manufaktur.de
Tel.: +49 5222 807110

Geschäftsführer Oliver Woineck
Ust.ID.Nr. DE303690847
Handelsregister Amtsgericht Lemgo, HRB 8618

- **500 metre range**
- The interference-free radio connection up to 500 metres in free field guarantees a reliable door chime.
- **13 polyphonic melodies**
- With the large selection of appealing ringtones, you can personalise your Calima 400 with complete flexibility.
- **Multiple call differentiation for several doors**
- With the help of call differentiation, you can immediately recognise whether the front door or the garden gate has rung. Up to 11 wireless bell buttons can be programmed and 11 can be assigned an individual ring tone.
- **Optical LED signal**
- LED ring with colour selection for visual signalling and night light function.
- **Adjustable night light function**
- Night light in desired colour.
- **Menu navigation with voice prompt**
- Each menu step is played back to you as a voice announcement.

### Notes

- Walls, doors, metal parts etc. can noticeably reduce the range!
- An additional transmitter (not included) is required for this receiver! See accessories.

## Dimensions

| | |
|---|---|
| **Width in mm** | 60 |
| **Height in mm** | 60 |
| **Total width in mm** | 60 |
| **Depth in mm** | 95,0 |

Briefkasten Manufaktur Lippe GmbH
Werler Straße 60
32105 Bad Salzuflen

www.briefkasten-manufaktur.de
info@briefkasten-manufaktur.de
Tel.: +49 5222 807110

Geschäftsführer Oliver Woineck
Ust.ID.Nr. DE303690847
Handelsregister Amtsgericht Lemgo, HRB 8618

# More images








Briefkasten Manufaktur Lippe GmbH
Werler Straße 60
32105 Bad Salzuflen

www.briefkasten-manufaktur.de
info@briefkasten-manufaktur.de
Tel.: +49 5222 807110

Geschäftsführer Oliver Woineck
Ust.ID.Nr. DE303690847
Handelsregister Amtsgericht Lemgo, HRB 8618