Gira built-in loudspeaker

Product number 125800



Product description

GIRA built-in loudspeaker 125800

Built-in loudspeaker for mounting in letterbox systems, intercom compartments, door side installations or front panels. Up to 8 mechanical bell buttons can be connected to the existing screw terminals.

- Built-in loudspeaker for mounting in letterbox systems, intercom compartments, door side installations or front panels.
- Up to eight mechanical bell buttons can be connected to the existing screw terminals.
- Signal transmission and power supply to the loudspeaker via the reverse-polarity protected and short-circuit-proof 2-wire bus.
- Small design.
- Weatherproof loudspeaker.
- High-quality electret microphone.
- AC voltage monitoring of the bell button connections to prevent oxidation on the button contacts.
- Protection of the connection terminals against incorrect connection.
- Up to eight mechanical bell buttons can be connected.
- Colour camera for door station can be connected.
- Hands-free function (voice-controlled intercom with echo and background noise cancellation).
- Speech volume adjustable.
- One-man commissioning thanks to simple commissioning procedure.
- Acoustic acknowledgement signal when call button is pressed.

Technical data

Power supply: 26 V DC ± 2 V (bus voltage)

Briefkasten Manufaktur Lippe GmbH
Werler Straße 60
32105 Bad Salzuflen

www.briefkasten-manufaktur.de
info@briefkasten-manufaktur.de
Tel.: +49 5222 807110

Geschäftsführer Oliver Woineck
Ust.ID.Nr. DE303690847
Handelsregister Amtsgericht Lemgo, HRB 8618

Connections:
2 screw terminals
2-wire bus
2 screw terminals Additional supply
8 screw terminals for mech. bell button
1 screw terminal common earth of the bell buttons
2 connector strips System bus
1 video connector strip

Temperature range: -25 °C to +70 °C
Protection class: IP 44

Notes

- This component can be used to set up door communication systems with up to 140 audio users (e.g. 1 x built-in loudspeaker, 11 x extension module for built-in loudspeaker, 136 x surface-mounted home station).
- A video control device is required when adding a colour camera.

Dimensions

Width in mm	101
Height in mm	67
Depth in mm	27,0
Weight in kg	0,2

More images


GIRA
CE
Türkommunikations-System
Einbaulautsprecher
1258 00
System
System
BUS
ZV